

Bridgemate® II

The next generation scoring system

Bridgemate II is the latest addition to the popular and widely-used Bridgemate Scoring System. Bridgemate Pro is used by more than 2,500 clubs in 35 countries; it is the premier scoring system of 25 national bridge organizations, the World Bridge Federation and European Bridge League. Built on a ten-year track record of proven reliability, Bridgemate II offers even more functionality and user-friendliness, all in a modern and slim design.



Key features

A modern and ergonomic design which fits perfectly on every bridge table. It's light weight and significantly reduced volume make it easy to carry and store.

It has the same large keys as Bridgemate Pro with four added function keys for unlimited extra functionality.

Large LCD screen; three times bigger than Bridgemate Pro and bigger than any other scoring system. Large and clear fonts make it easily readable for players of all ages.

An intuitive entry process of board results requiring only a minimum of key strokes. All information for each board is entered on one screen.

Very low battery consumption. Bridgemate II typically runs about 500 sessions on one set of 2 AA batteries and is therefore very economical¹.

Easy to clean and maintain due to its snap-on cover. The cover can be removed in just seconds to allow cleaning or keypad replacement.

Functionality

Bridgemate II offers you all the functionality of Bridgemate Pro plus many new features which make the game even more attractive. New functions are:

- Entry of board data all on one screen.
- Confirmation of score by East/West using a dedicated "accept" key.
- During a round, players may review their own scores at any time, and – TD option - edit these scores.
- Real-time movement synchronization ensures that movement updates made in your scoring program are immediately relayed to the Bridgemates.
- Update Bridgemate settings at any time during play – for all (or selected) tables/sections.
- Show previous board results as traveller or frequency list, either 4 (large font) or 6 (medium-sized font) scores per screen. Browse through the results with up and down function keys.
- TD-menu is accessible using a function key and requires entry of a self-configurable PIN code.
- Show current ranking during play, or at end of session only².
- Show player names at start of each round².
- Show IMP instead of percentages as indication of board result².
- Show seatings for next round.
- Show remaining boards to be played in current round.
- Setup menu for configuring basic settings.
- Scan function for choosing between available sections in play.
- Easy software updates through wireless transfer.

External layout of Bridgemate II



Ergonomic design which fits easy in the hand or sturdily sits on the table.

← Large size LCD screen: 2.5" x 1.5"

← Four function keys for additional functionality

← Large keys with clear printing

Comparison table Bridgemate Pro and Bridgemate II

<i>Description of function/feature</i>	<i>Bridgemate Pro</i>	<i>Bridgemate II</i>
Keyboard	25 keys	25 keys + 4 function keys
Screen	2 lines of 16 characters	Graphical display. Between 4 and 10 lines of text
Batteries	4 x AAA	2 x AA
Number of sessions on one set of batteries ¹	Approx. 350	Approx. 500
Selection of section/table at start of session	✓	✓
Scan for available sections at start of session	✗	✓
Entry of contract & result	✓	✓
Entry of lead card	✓	✓
Entry of player numbers at start of session	✓	✓
Show player names at start of round	✗	✓ ²
Automatic entry of board number	✗	✓
Verification of board order	✓	✓
Confirmation of score by East/West	OK key	Dedicated "accept" key
Players can review and edit their scores	✗	✓
Show percentage of board result	✓	✓
Show IMP of board result	✗	✓ ²
Show remaining boards to be played	✗	✓
Overview of previous board results	Individual scores, 2 per screen	Individual scores or frequency list. 4 or 6 per screen
Show seatings for next round	✗	✓
Show current ranking	✗	✓ ²
Access to TD-menu	TD-key	PIN code
Confirmation of "Not played" by TD	✗	✓
Update Bridgemate option settings during play	✗	✓
Software update method	data cable	wireless transfer

¹ Based on Duracell alkaline batteries, 26 boards per session and activation time of approximately two minutes per board. Number of sessions may be lower due to self-discharge during long periods of inactivity.

² Not available in first release. Feature will become available through free, firmware update.